

## **Power generator *R-Power GE 5000***

|                          |                    |
|--------------------------|--------------------|
| Engine                   | General Engine     |
| Engine type              | 4 stroke           |
| Engine power             | 13 HP              |
| Cylinder capacity        | 389 cc             |
| Ignition system          | Electronic         |
| Start-up                 | Manual             |
| Fuel                     | Unleaded gasoline  |
| Fuel tank capacity       | 6.5 l              |
| Average fuel consumption | 0.33 (liters/Kw/h) |
| Output voltage DC        | 12 V               |
| Output voltage AC        | 220                |
| Maximum generator power  | 5500W              |
| Generator rated power    | 5000W              |
| Working frequency        | 50 Hz              |
| Number of outlets        | 2                  |
| Stator, rotor winding    | Copper             |
| Analog voltmeter         | Standard equipment |
| Fuse                     | Standard equipment |
| Frame type               | Industrial         |
| Weight                   | 65 kg              |
| Warranty                 | 24 months          |