

Power generator RURIS R-POWER

GE5500

Engine	General Engine
Engine type	4 stroke
Engine power	13 hp
Cylinder capacity	420 cc
Ignition system	Electronic
Start-up	Manual
Fuel	Unleaded gasoline
Fuel tank capacity	25 L
Oil bath capacity	1.1 L
Average fuel consumption	< 374 (grams/kW/h)
Maximum generator power	5500 W
Generator rated power	5000 W
Working frequency	50 Hz
Rated current/ A	23
Number of outlets	2
Stator, rotor winding	Copper
Output voltage DC	-
Output voltage AC	220 V
AVR	YES
Fuse	Standard equipment
Frame type	Industrial
Weight	70 kg