

## Power generator **R-Power GE 8000**

|                                 |                       |
|---------------------------------|-----------------------|
| <b>Engine</b>                   | General Engine        |
| <b>Engine type</b>              | 4 stroke              |
| <b>Engine power</b>             | 14 HP                 |
| <b>Cylinder capacity</b>        | 459 cc                |
| <b>Ignition system</b>          | Electronic            |
| <b>Start-up</b>                 | Electric with battery |
| <b>Fuel</b>                     | Unleaded gasoline     |
| <b>Fuel tank capacity</b>       | 28 l                  |
| <b>Engine oil bath capacity</b> | 1.1 l                 |
| <b>Average fuel consumption</b> | 0.472 (liters/Kw/h)   |
| <b>Output voltage DC</b>        | 12V / 8.3A            |
| <b>Output voltage AC</b>        | 3 phases-<br>230/400V |
| <b>Maximum power</b>            | 7500 W                |
| <b>Rated power</b>              | 7000 W                |
| <b>Rated current / A</b>        | 10.1                  |
| <b>Performance class</b>        | G1                    |
| <b>Working frequency</b>        | 50 Hz                 |
| <b>Number of outlets</b>        | 2                     |
| <b>Stator, rotor winding</b>    | Copper                |
| <b>Analog voltmeter</b>         | Standard              |
| <b>Fuse</b>                     | Standard              |
| <b>Frame type</b>               | Industrial            |
| <b>Transport wheels</b>         | YES                   |
| <b>Weight</b>                   | 88 kg                 |
| <b>Warranty</b>                 | 24 months             |