

## **Power generator *R-Power GE 2500***

<b>Engine</b>	General Engine
<b>Engine type</b>	4 stroke
<b>Engine power</b>	7 HP
<b>Cylinder capacity</b>	196 cc
<b>Ignition system</b>	Electronic
<b>Start-up</b>	Manual
<b>Fuel</b>	Unleaded gasoline
<b>Fuel tank capacity</b>	3.6 l
<b>Average fuel consumption</b>	0.33 (liters/Kw/h)
<b>Output voltage DC</b>	12 V
<b>Output voltage AC</b>	220
<b>Maximum generator power</b>	2800 W
<b>Generator rated power</b>	2500 W
<b>Working frequency</b>	50 Hz
<b>Number of outlets</b>	2
<b>Stator, rotor winding</b>	Copper
<b>Analog voltmeter</b>	Standard equipment
<b>Fuse</b>	Standard equipment
<b>Frame type</b>	Industrial
<b>Weight</b>	47 kg
<b>Warranty</b>	24 months